

Technical Bulletin
SIRIUS Stiletto 2 – Software Release 2.0.2
December 19, 2007

SIRIUS has made a few key improvements to the Stiletto 2 software recently. These will be made available to all subscribed Stiletto 2 units through a field deliverable software upgrade. Taking advantage of these enhancements is fast and easy - just follow the directions below to download and install the new v 2.0.2 software.

This upgrade will be available starting immediately, though due to increased network traffic, delivery of the upgrade will be temporarily suspended between December 24th thru December 27th

Updated units will display the following versions:

Product Model	ZAP	OS	Bootloader	Baseband
Stiletto 2	2.0.2.5118	2.0.2.50304	2.0.x.varies	00.14.94

What's Included in the Release

SIRIUS Stiletto 2 version 2.0.2 contains several feature enhancements, as well as fixes for some software bugs found in the 2.0.0 release.

Enhanced Features

- Improved support for captive portals found at WiFi hotspots
- A warning message is now displayed for users attempting to 'Sync' from a SLH2 home dock if no USB cable is connected
- Display of longer WiFi network names (SSID)
- Improved system stability

Bug Fixes

- Reduced incidence of "acquiring signal" and "antenna not detected" messages while the radio is installed in the Stiletto Vehicle dock (SLV2)
- Improved audio quality and distortion reduction
- Reduced incidence of long block recording and Radio Replay corruption

How to Get this Release

Updating over WiFi:

Subscribers may update Stiletto 2 over WiFi by following these steps:

1. Turn on the Stiletto 2 and press the **HOME** button
2. Use the **MEDIA DIAL** to scroll to Internet Radio
3. Press the **SELECT** button to connect to Internet Radio

4. Tune to your favorite station and let it play for several hours
5. The software will download automatically. Once received follow the screen prompts to complete the update.

Updating using My Sirius Studio™:

Customers without WiFi access may update using My Sirius Studio™ running on a PC with an active internet connection:

1. Launch My Sirius Studio™ on your computer
2. Connect the Stiletto 2 to your computer using the USB cable supplied with your device
3. In My Sirius Studio, click on the gear icon next to the device or go to **File** → **Device Settings** → **Check for Software Update**.
4. Follow the instructions that appear in My Sirius Studio™ to complete the update.

Please Note: During the update, your media library must be re-built. If you have a large amount of content stored on an installed microSD™ card, the process can last for as long as 10 minutes. During this time the message “microSD card installed” will be displayed.

For additional questions regarding your Stiletto 2 or the SIRIUS service, please refer to the product manuals. You can also reach the dedicated Stiletto Technical Support Team at 1-800-869-5364 from 10 AM to 10 PM Eastern Time Monday through Saturday, or by email at customercare@sirius-radio.com.